



Cordless Blower DUB361

Delivers up to 73 minutes of run time using two 4.0Ah 18V LXT batteries on low speed setting

Powered by two 18V Li-ion batteries in series



Makita-built motor produces a maximum air velocity of 93 m/s. Variable 2-speed (0-10,000 & 0-17,000 RPM) design for optimum speed control



CONVENIENCE

Zero emissions and reduced maintenance for increased ease of use

POWER

Makita-built motor produces a maximum air velocity of 208 MPH



INNOVATION

Two 18V LXT® Lithium-Ion batteries deliver the power and run time for corded demands

POWER

Makita-built motor produces a maximum air velocity of 208 MPH

<p>Cordless Blower</p>	Electronic 2-Speed	<p>Max Air Volume</p> <p>High: 4.4 m³/min (155 CFM) Low: 2.6 m³/min (92 CFM)</p>	430
		<p>Max Air Velocity</p> <p>High: 93 m/s (208 MPH) Low: 57 m/s (128 MPH)</p>	
		<p>No Load Speed (RPM)</p> <p>High: 17,000 Low: 10,000</p>	
		<p>Sound Pressure Level 82.3 dB(A) Sound Power Level 94.7 dB(A) Noise K Factor 1.6 dB(A)</p>	
		<p>Vibration Level 2.5 m/s² or less Vibration K Factor 1.5 m/s²</p>	
		<p>Dimensions (L x W x H) 905x141x194 mm (35-5/8"x5-5/8"x7-5/8") Net weight 3.1 - 3.2 kg (6.8 - 7.1 lbs.)</p>	
<p>Standard Equipment : Shoulder Belt, Nozzle, Battery, Charger</p>			



Makita Power Tools India Pvt. Ltd.

Unit II Sy. Nos. 93/3 & 93/4, Koralur village, Kasaba Hobli, Hoskote Taluk, Bangalore - 560 067, INDIA. Tel: +91 80 2854 9008, Fax: +91 80 2854 9007
Email: sales@makita.in Website: www.makita.in

