





Li-ion In-Line Cordless Screwdriver DF001DW (with 81 pcs bit assortment and Charger)



LED job light



ON / OFF switch with reverse / forward control



USB connector with rubber cover

pistol style

Can be used as both of straight style and pistol style

straight style



Can be used as a hand Screwdriver

Comes with 81pcs assortment and Charger



Convenient in a narrow space

Drive type

Phillips (PH)	PZ	Hex (H)
T	Slotted (SL)	

C-form 25mm Screw bit

PZ : 0, 1, 2, 3 (3pc each)
 Hex : 2, 2.5, 3, 4, 5, 6 (2pc each)
 T : 10, 15, 20, 25, 27, 30, 40 (3pc each)
 SL : 0.5x3, 0.5x4, 0.6x4.5, 0.8x5.5, 1.0x5.5, 1.2x6.5 (2pc each)
 PH : 0, 1, 2 (3pc each), 3 (2pc each)

Charger (ADP07)

Charging time: 3 to 5 hours (DC5V/ 1A USB output)



E-form 50mm Screw bit

T : 20, 25, 30 (1pc each)
 PH : 1, 2, 3 (1pc each)

E-form Socket Wrench

5, 6, 7, 8, 9, 10mm (1pc each)

E-form magnetic bit holder

60mm (1pc each)

In-Line Cordless Screwdriver DF001D

- Reversing
- Built-in Job Light
- Carrying Case

Fastening Capacities	Wood Screw: $\phi 3.8 \times 32$ mm (1/8" x 1-1/4")
No Load Speed (RPM)	220
Max Fastening Torque	Hard / Soft: 4.0 / 3.0 N·m (35 / 27 in.lbs.)
Max lock torque	6.0 N·m (53 in.lbs.)
Vibration Level	Screwdriving without Impact: 2.5 m/s ² or less
Sound Pressure Level	70 dB(A) or less
Charging Time (hours)	3 - 5
Dimensions (L x W x H)	Straight style: 287x47x51mm (11-1/4"x1-7/8"x2") Pistol style: 205x47x51mm (8-1/8"x1-7/8"x2")
Net weight	0.36 kg (0.8 lbs.)

Standard Equipment : DF001DW: Bit set (81 pcs), Charger, USB Cable

weight according to EPTA-Procedure 01/ver.2.1
 Items of standard equipment and specifications may vary by country or area.

Makita Corporation

3-11-8 Sumiyoshi-cho, Anjo, Aichi, 446-8502 Japan

PRINTED IN JAPAN 201701