





Rotary Hammer

□ Double Insulation Variable Speed

Constant Speed Soft Start

Carrying Case



Torque Limiter

Continuous rating Input Capacity

Impacts per minute (ipm)

Dimensions (LxWxH)

Power supply cord

HR4013C AVT & SOFT NO LOAD

HR4013C / HR4003C 40mm (1-9/16")Adapted for SDS-MAX bits

1,100W Concrete (with T.C.T. bit) : 40mm (1-9/16") 1.450 - 2.900

479x112x263mm (18-11/16"x4-3/8"x10-3/8")

HR4003C

1,100W Concrete (with T.C.T. bit) : 40mm (1-9/16") 1.450 - 2.900

479x106x263mm (18-11/16"x4-3/16"x10-3/8")

Standard Equipment: Depth Gauge, Side Handle, Bit Grease(Tool does not come with bit.)

Makita Corporation

3-11-8 Sumiyoshi-cho, Anjo, Aichi, 446-8502 Japan

PRINTED IN JAPAN BD-AJ

350



ANTI VIBRATION TECHNOLOGY

Comparison of Vibration level* and Time to reach ELV (Exposure Limit of Vibration)**

HR4013C 5.0m/s² 480min. 7.5m/s^2 213min. **Predecessor Model** 10m/s² 120min. Competitor "B"


*It is known as the tri-axial value and value at Directive of A(8). **It means the maximum amount of vibration that an operator

may be exposed to on any single day.

Unrivalled low level of vibration


Vibration absorbing housing (HR4013C)


This is the new AVT mechanism advanced from the current "Vibration absorbing handle". The level of vibration is further reduced by completely separating the machine holding section from the motor/transmission section






ensures operation with extremely low vibration. allows tool design with flat body sides for better handling.





Damper spring

the moment of impact.





Adapted for SDS-MAX bits

absorbs reaction force caused by drill bit at





T Lock-on switch for continuous chiseling applications

> Trigger switch for intermittent chiseling applications



Rotation with hammering Bit angle settings




Photo: HR4013C (Tool does not come with bit.)

with bull point

Compared with our predecessor model

with 32mm diameter bit

Soft no load" function (HR4013C)



- minimizes deflection of bit tip from aiming point when starting chipping.





