



# Cordless Angle Screwdriver DFL063F

Conveniently located forward/reverse push button switch for easy operator access




## Cordless Angle Screwdriver




 Variable Speed

 Brake

 Reversing

 Constant Speed

 Soft Start

 Built-in Job Light

### Standard Equipment:

Torque Adjust Tool (country-specific), USB Cable (country-specific), Protector (country-specific)

<b>Max Output</b>	390 W
<b>Driving Shank (Square)</b>	9.5 mm (3/8")
<b>No Load Speed (RPM)</b>	180 - 1,300
<b>Fastening Torque</b>	Hard / Soft: 1.5 - 6.5 / 1.5 - 6.5 N·m (13 - 58 / 13 - 58 in.lbs.)
<b>Vibration Level</b>	Screwdriving w/o Impact: 2.5 m/s <sup>2</sup> or less
<b>Vibration K Factor</b>	Screwdriving w/o Impact: 1.5 m/s <sup>2</sup>
<b>Sound Pressure Level</b>	70 dB(A)
<b>Noise K Factor</b>	3 dB(A)
<b>Dimensions (L x W x H)</b>	w/ BL1815N / BL1820B: 380x74x116 mm (15"x2-5/16"x4-9/16")
	w/ BL1830B / BL1840B / BL1850B / BL1860B: 397x74x116 mm (15-5/8"x2-5/16"x4-9/16")
<b>Head Height</b>	25 mm (1")
<b>Center Height</b>	11 mm (7/16")
<b>Net weight</b>	1.3 - 1.7 kg (2.9 - 3.8 lbs.)



## Makita Power Tools India Pvt. Ltd.

Unit II Sy. Nos. 93/3 & 93/4, Koralur village, Kasaba Hobli, Hoskote Taluk,  
Bangalore - 560 067, INDIA. Tel: +91 80 2854 9008, Fax: +91 80 2854 9007  
Email: sales@makita.in Website: www.makita.in