



# Cordless Grease Gun XPG01Z

Satisfy Professional's Needs







## Powerful motor delivers up to 69 MPa (10,000 PSI) of max pressure



### Cordless Grease Gun



-  Variable Speed
-  Soft Start
-  Carrying Case

<b>Max Operating Pressure</b>	69 MPa (10,000 PSI)	
<b>Flow Rate</b>	Slow Speed Mode: 145 mL/min (5.0 oz/min) Auto Speed Change Mode: 290 mL/min (10.0 oz/min)	
<b>Grease Capacity w/ Barrel A</b>	Cartridge / Bulk: 410 / 455 g (14.5 / 16.0 oz)	
<b>Grease Capacity w/ Barrel B</b>	Cartridge / Bulk: 450 / 570 g (15.9 / 20.1 oz)	
<b>Grease Capacity w/ Barrel C</b>	Cartridge / Bulk: 500 / 570 g (17.6 / 20.1 oz)	
<b>Hose Length</b>	120 cm (47-1/4")	
<b>Max Output</b>	480 W	
<b>Vibration Level</b>	2.5 m/s <sup>2</sup> or less	
<b>Vibration K Factor</b>	1.5 m/s <sup>2</sup>	
<b>Sound Pressure Level</b>	76 dB(A)	
<b>Dimensions (L x W x H)</b>	w/ Barrel A: 411 x 114 x 245 mm (16-1/4 x 4-1/2 x 9-5/8")	
<b>Net weight</b>	4.8 - 6.1 kg (10.6 - 13.4 lbs.)	

**Standard Equipments:** Shoulder Strap, Battery, Charger



### Makita Power Tools India Pvt. Ltd.

Unit II Sy. Nos. 93/3 & 93/4, Korallu village, Kasaba Hobli, Hoskote Taluk,  
Bangalore - 560067, INDIA. Tel: +91-80-2222-8200  
Email: info@makita.in Website: www.makita.in

